


LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I²C communication

The PAJ7620U2 is a highly integrated gesture-recognition sensor module from Pixart that detects up to nine hand gestures and proximity via an I²C interface. It is commonly available on breakout boards for use with microcontrollers such as Arduino or Raspberry Pi.



The sensor module integrates an optical lens and an infrared (IR) LED to function even in low-light or dark environments.

Key Features

- **Supported Gestures:** 9 basic gestures: Up, Down, Left, Right, Forward, Backward, Clockwise (CW) circle, Counter-clockwise (CCW) circle, and Wave. Some modules support up to 13 gestures in a slower mode.
- **Interface:** I²C communication interface (up to 400 kbit/s), default address: **0x73**
- **Operating Voltage:** Typically 2.8V to 3.6V (sensor chip); breakout boards often include onboard voltage translators for 3.3V/5V compatibility. If using a basic breakout board without a voltage regulator, connect a 3.3V supply to the VCC pin. If using a module that specifies 5V compatibility (such as the Waveshare or Gravity series), you can safely use either 3.3V or 5V.
- **Detection Distance:** Effective range of 5 cm to 15 cm, with some setups reaching up to 20 cm.
- **Ambient Light Immunity:** High immunity to ambient light, up to <100k Lux.
- **Power Consumption:** Designed for low-power operation, suitable for battery-operated devices.
- **Array Size:** 60×60 pixels
- **Gesture speed:** 60~600°/s in Normal Mode and 60~1200°/s in Gaming Mode



If you'd like to support the development of the site with the price of a coffee — or a few — [please do so here](#).

Here's a handy tip: you can quickly save this page as a PDF by clicking "export to PDF" in the menu on the right side of the screen.

2026/02/14 23:38

Arduino wiring

- SCL: A5

- GND: GND
- SDA: A4
- Vdd: 5V

Arduino code

Here is the example code that uses the **RevEng PAJ7620** Library to recognize 9 gestures:

```
#include "RevEng_PAJ7620.h"

RevEng_PAJ7620 sensor = RevEng_PAJ7620();

void setup() {
  Serial.begin(9600);
  if (!sensor.begin()) {
    Serial.print("PAJ7620U2 initialization failed");
  }
}

void loop() {
  Gesture gesture = sensor.readGesture();

  switch (gesture) {
    case GES_FORWARD:
      Serial.println("FORWARD");
      break;
    case GES_BACKWARD:
      Serial.println("BACKWARD");
      break;
    case GES_LEFT:
      Serial.println("LEFT");
      break;
    case GES_RIGHT:
      Serial.println("RIGHT");
      break;
    case GES_UP:
      Serial.println("UP");
      break;
    case GES_DOWN:
      Serial.println("DOWN");
      break;
    case GES_CLOCKWISE:
      Serial.println("CLOCKWISE");
      break;
    case GES_ANTICLOCKWISE:
      Serial.println("ANTICLOCKWISE");
      break;
    case GES_WAVE:
      Serial.println("WAVE");
      break;
  }
}
```

```
}
}
```

I²C topics on lamaPLC

| Page | Date | Tags |
|---|---------------------|--|
| • lamaPLC Communication: 1-Wire | 2026/04/23 21:51 | 1-wire , communication , bus , microlan , i2c , uart , usart , ds18b20 |
| • lamaPLC Communication: I²C | 2025/09/23 21:25 | i2c , i c , smbus , philips , bus , communication , arduino |
| • lamaPLC project: Sension SCD CO² measurement module | 2026/04/15 19:34 | scd30 , scd40 , scd41 , iaq , ndir , sensor , i2c , arduino code |
| • LamaPLC: AHT10 Modul | 2026/03/22 03:14 | communication , i2c , temperature , humidity , sensor , aht , aht 10 , modul |
| • LamaPLC: AHT20 / BMP280 Modul | 2026/04/23 21:52 | bmp280 , aht20 , adafruit , temperature , humidity , pressure , sensor , arduino , code , i2c |
| • LamaPLC: APDS - Avago ALS and proximity detection sensors with I²C communication | 2026/04/23 21:52 | avago , apds-9900 , apds-9930 , apds-9960 , als , proximity , detection , gesture recognition , gesture , i2c , communication , sensor , arduino , code |
| • lamaPLC: Arduino Modul: BME680 | 2026/05/12 18:40 | code , c , 2026 , arduino , bme680 , sensor , i2c , comunication |
| • lamaPLC: AS5600 Magnetic Induction Angle Measurement Sensor Module | 2026/05/13 00:06 | communication , i2c , as5600 , as-5600 , magnetic , induction , angle , sensor |
| • lamaPLC: Bi-Directional Logic Level Converter 3.3V ↔ 5V | 2026/04/12 00:34 | bi-directional , logic level converter , i2c , uart , spi |
| • LamaPLC: BMP/BME Bosch Temperature/Humidity/Pressure sensors with I²C communication | 2026/04/23 21:52 | bme280 , bme680 , bme688 , bmp180 , bmp280 , hw-611 , hw611 , bosch , temperature , humidity , pressure , sensor , arduino , i2c , communication , ai , cjmcu , volatile organic compounds , vocs , volatile sulfur compounds , vscs , iaq |
| • LamaPLC: CJMCU-219/INA-219 breakout board/IC with I²C communication | 2026/04/23 21:52 | cjmcu-219 , ina-219 , ina219 , breakout board , i2c , communication , sensor , voltage , current , arduino , code , cjmcu |
| • LamaPLC: CJMCU-3216 / AP-3216 integrated digital ambient light and proximity sensor module/IC with I²C communication | 2026/04/23 21:52 | cjmcu-3216 , cjmcu , ap-3216 , ap3216 , ambient light , proximity , sensor , arduino , code , i2c , communication |
| • lamaPLC: CJMCU-811 CCS811 Gas Sensor (VOCs TVOC CO₂) | 2026/04/23 21:52 | cjmcu-811 , ccs811 , gas , sensor , vocs , tvoc , eco2 , co2 , arduino , air quality , metal oxide , mox , i2c , micropython , rp2040-eth |
| • LamaPLC: D6T Omron Non-Contact Thermal Sensors with I²C communication | 2026/04/23 21:52 | d6t , d6t-32l , d6t-44l , d6t-8l , d6t-1a , omron , non-contact , thermal , sensor , i2c , arduino , code |

- [LamaPLC: DPS Infineon Temperature/Pressure sensors with I2C communication](#) 2026/04/23 21:52 [dps310, infineon, temperature, pressure, sensor, arduino, i2c, communication, code](#)
- [lamaPLC: Energy, power, current, and voltage](#) 2025/05/31 23:32 [i2c, i c, communication, arduino, energy, power, current, sensor, ina226 ens160, sciosense, gas-quality, i2c, communication, sensor, arduino, code, eco2, tvoc, aqi, indoor air quality, iaq, co2, voc](#)
- [LamaPLC: ENS ScioSense Multi-gas sensors with I²C communication](#) 2026/04/23 21:52 [esp8266, esp32, esp32-c2, esp32-c3, esp32-c5, esp32-c6, esp32-c61, esp32-h2, esp32-s2, esp32-s3, esp32-p4, espressif systems, communication, ethernet, ip, wi-fi, thread, zigbee, matter, homekit, bluetooth, mqtt, adc, spi, uart, i2c, i2s, rmt, pwm, usb, usb otg, twai](#)
- [lamaPLC: ESP32 / ESP8266](#) 2025/11/22 00:07 [gas, sensor, i2c, onewire, communication, mq-3, mq-4, mq-5, mq-6, mq-7, mq-8, mq-9, mq-135, gm-102b, gm-302b, gm-502b, gm-702b, alcohol, ch4, natural gas, smoke, lng, co, co2, lpg, h2, iso-butane, nox, nh3, benzene, town gas, formaldehyde, propane, humidity, temperature, voc, grv gas sens v2](#)
- [LamaPLC: Gas sensors](#) 2023/07/01 17:29 [stmicroelectronics, lsm303dlhc, i2c, lsm303, sensor, gy-511, 6dof, pololu, module, arduino](#)
- [lamaPLC: GY-511 6DOF sensor module](#) 2026/04/23 21:52 [ak8963, gy-9250, mpu-9250, 9-axis, motion detection, magnetometer, communication, i c, i2c, spi](#)
- [LamaPLC: GY-9250 MPU-9250/6500 9-axis Attitude Sensor Board](#) 2026/04/23 21:52 [sht21, htu21, si7021, gy-21, gy-213v, hdc1080, gy-213v-hdc1080, cjmcu, cjmcu-1080, texas instruments, temperature, humidity, sensor, i2c, communication, arduino, code](#)
- [LamaPLC: HDC Texas Instruments Temperature/humidity sensors with I²C communication](#) 2026/04/23 21:52 [i2c, 7-segment display, display, ht16k33, arduino](#)
- [lamaPLC: HT16K33 display controller](#) 2026/04/23 21:51 [htu, htu31d, htu21d, htu20d, sht20, htu20, sht21, htu21, si7021, gy-21, gy-213v, hdc1080, si702, gy-20, sht31, htu31, si7031, gy-31, te connectivity, temperature, humidity, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: HTU TE Connectivity temperature/humidity sensors with I²C communication](#) 2026/04/23 21:52 [i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina219, gy-219, ina226, gy-216, ina228, gy-228, ina237, ina238, ina260, ina3221, ina](#)
- [lamaPLC: INA modules with Arduino libraries](#) 2026/04/23 21:52 [i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina](#)
- [lamaPLC: INA226 - current/voltage/power monitor with I²C communication](#) 2026/04/23 21:52 [i2c, i c, communication, arduino, energy, power, current, monitor, sensor, ina226, ina219, ina](#)

| | | |
|---|---------------------|--|
| • lamaPLC: LCD 1602/2004 with I ² C communication | 2026/02/14 18:27 | communication, i2c, display, lcd, 1602, 2004, hd44780, pcf8574, pcf8574t, pcf8574at, arduino |
| • LamaPLC: MAX30100/MAX30102 Heart Rate Click Sensor Module | 2026/04/23 21:52 | max30102, max30100, heart rate click, sensor, communication, i2c, arduino, code |
| • lamaPLC: MCP23017 / MCP23S17 16-Bit I/O Expander with Serial Interface I ² C / SPI | 2026/04/23 21:52 | communication, i2c, mcp23017, mcp23s17, spi, i o expander, serial, cjmcu-2317, cjmcu |
| • lamaPLC: MLX90614 (GY-906) infrared non-contact thermometer | 2026/05/08 00:03 | communication, i2c, temperature, mlx90614, gy-906, modul, infrared, non-contact thermometer, dsp, pwm, smbus, hailege |
| • lamaPLC: PCF857x I/O Expander chip/modul with I ² C communication | 2026/05/15 01:03 | communication, i2c, pcf857x, pcf8574, pcf8574a, pcf8575, i o expander, i o extension, nxp, texas instruments |
| • LamaPLC: Pixart PAJ7620U2 Gesture recognition sensors/module with I ² C communication | 2026/04/23 21:52 | paj7620u2, gy-paj7620, pixart, gesture recognition, i2c, communication, sensor, arduino, code |
| • lamaPLC: RP2040_ETH_Modul: I ² C scanner | 2026/05/12 16:20 | code, micropython, 2026, rp2040 eth, i2c, comunication |
| • lamaPLC: RP2040_ETH_Modul: MLX90614 simple | 2026/05/12 17:06 | code, micropython, 2026, rp2040 eth, i2c, communication, mlx90614 |
| • lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data | 2026/05/12 21:06 | code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication |
| • lamaPLC: RP2040_ETH_Modul: Read BME 680/688 sensor data and store in Modbus input registers | 2026/05/12 18:58 | code, micropython, 2026, rp2040 eth, bme680, i2c, sensor, communication |
| • LamaPLC: SC16IS750 / SC16IS752: One or two serial (UART) ports from microcontroller via I ² C or SPI communication | 2026/04/23 21:52 | cjmcu-750, cjmcu-752, cjmcu, nxp, sc16is750, sc16is752, uart, serial, i2c, spi, modul, converter, arduino, code |
| • LamaPLC: SGP Sensirion TVOC/VOC sensors with I ² C communication | 2026/04/15 19:41 | sgp30, sgp40, sgp41, sensirion, gas-sensor, i2c, communication, sensor, arduino, code, eco2, voc, tvoc, indoor air quality, iaq, nox, hydrogen |
| • LamaPLC: SHT Sensirion Temperature/humidity sensor with I ² C communication | 2026/04/23 21:52 | sht20, sht21, sht25, sht30, sht31, sht35, sht40, gy21, temperature, humidity, i2c, communication, sensor, arduino, code |
| • lamaPLC: Signal level converters | 2026/02/14 23:47 | pca9306, i2c, voltage, level, converter |
| • lamaPLC: st756x display drivers | 2026/05/20 16:17 | display, driver, i2c, spi, lcd, cog, oled, st7565, st7567, gm12864, gm12864-59n, gm12864-03a, gm12864-01a, gme12864-41 |
| • lamaPLC: TCA9548A (HW617); Low-Voltage 8-Channel I ² C Switch Module | 2026/02/14 23:51 | tca9548a, hw617, i2c, switch, communication, expansion board, arduino |
| • lamaPLC: TM1637 7-segment display | 2026/02/14 18:26 | i2c, 7-segment display, display, tm1637, arduino |

- [LamaPLC: TOFnnnC STMicroelectronics Time-of-Flight \(ToF\) sensors with I²C communication](#) 2026/04/23 21:52 [tof050c, vl6180, tof200c, vl53l0x, tof400c, vl53l1x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL53Lnn STMicroelectronics time-of-flight \(ToF\) laser-ranging sensors with I²C communication](#) 2026/04/23 21:52 [vl53l0x, vl53l1x, vl53l0 1xv2, gy-530, time-of-flight, tof, laser-ranging, i2c, communication, sensor, arduino, code](#)
- [LamaPLC: VL6180X STMicroelectronics Time-of-Flight \(ToF\) sensor with I²C communication](#) 2026/04/23 21:52 [vl6180x, stmicroelectronics, time-of-flight, tof, i2c, communication, sensor, arduino, code](#)
- [lamaPLC: XGZP68xx: Silicon Pressure Sensors/Module](#) 2026/05/15 15:17 [communication, i2c, sensor, modul, pressure, cfsensor, xgzp68xx, xgzp6810d, xgzp6857d, xgzp6859d, xgzp6887d, xgzp6897d, xgzp6899a, piezoresistive, capacitive](#)
- [Magnetic angle sensors](#) 2026/03/05 21:19 [magnetic angle sensor, magnetic flux, sensor, spi, i2c, pwm, communication, modul, as5047p, as5600, mt6701, mt6816, mt6835, tle5012b, amr, gmr, tmr, anisotropic magnetoresistive](#)
- [SSH1106/SSD1306 OLED Display with I²C communication](#) 2026/02/14 18:27 [i2c, oled, display, ssd1306, sh1106, ssh1106, arduino, cmos](#)

[PAJ7620U2](#), [GY-PAJ7620](#), [Pixart](#), [gesture recognition](#), [i2c](#), [communication](#), [sensor](#), [arduino](#), [code](#)

This page has been accessed for: Today: 1, Until now: 172

From: <https://www.lamaplc.com/> - **lamaPLC**

Permanent link: <https://www.lamaplc.com/doku.php?id=sensor:paj>

Last update: **2026/04/21 20:47**

