

lamaPLC: PCF857x I/O Expander chip/modul with I²C communication

The PCF857x series consists of I²C-based general-purpose I/O (GPIO) expanders manufactured by NXP and Texas Instruments. They allow microcontrollers (such as Arduino, ESP32, or Raspberry Pi) to control multiple digital pins with only two wires: Serial Data (SDA) and Serial Clock (SCL).



Feature	PCF8574 / PCF8574A	PCF8575
GPIO Count	8-bit (8 pins)	16-bit (16 pins)
I²C Base Address	0x20 (PCF8574) / 0x38 (PCF8574A)	0x20
Max Devices on 1 Bus	8 units	16 units
Operating Voltage	2.5V to 6V	2.5V to 5.5V
Interrupt Output	Yes (Open-drain INT)	Yes (Open-drain INT)

The current limits of the PCF857x are heavily lopsided because of its quasi-bidirectional architecture. It handles current entirely differently depending on whether you are sinking current (outputting 0/LOW) or sourcing it (outputting 1/HIGH).

Main Control & Power Header

- **VCC:** Power input. Connects to **3.3V or 5V** to match your microcontroller's logic levels.
- **GND:** Common ground reference.
- **SDA:** Serial Data line for I²C communication.
- **SCL:** Serial Clock line for I²C communication.
- **INT:** Interrupt output (Active Low). Pulls low to alert the microcontroller when an input pin changes state, eliminating the need for software polling.

8/16-Bit I/O Extension Pins

- **Port 0** (P00 to P07): The first group of 8 quasi-bidirectional GPIO pins.
- **Port 1** (PCF8575 only, P10 to P17): The second group of 8 quasi-bidirectional GPIO pins.

Sinking Current (Output LOW / Connecting to Ground)

- **Maximum per individual pin:** 25 mA (typical) / 20 mA for extended use.
- **Maximum combined total (all 16 pins combined):** 100 mA.
- **The Math:** If you activate all 16 pins simultaneously at LOW logic, you can only allocate a maximum of 6.25 mA per pin ($100 \text{ mA} \div 16$) to avoid overloading the chip.

Sourcing Current (Output HIGH / Connecting to VCC)

This is the weak mode meant mostly for sensing state changes.

- **Maximum per individual pin:** Only 100 μ A (0.1 mA).
- **The Limit:** This current is too weak to directly light up an LED or actuate a standard relay trigger.

From:

<https://www.lamaplc.com/> - **lamaPLC**

Permanent link:

<https://www.lamaplc.com/doku.php?id=sensor:pcf857x&rev=1778766691>

Last update: **2026/05/14 15:51**

